



P1 { Alimentazione 12V: Jumper inserito
12V feed: connected Jumper
Alimentazione 24V: Jumper non inserito
24V feed: disconnected Jumper

S1 { Jumper in posiz. A: Buzzer suono continuo
Jumper in A pos.: Buzzer continuous sound
Jumper in posiz. B: Buzzer suono pulsante
Jumper in B pos.: Buzzer intermittent sound

S2 { Jumper in posiz. A: Led a luce fissa
Jumper in A pos.: Fixed light led
Jumper in posiz. B: Led a luce lampeggiante
Jumper in B pos.: Intermittent light led

Assorbimenti - Absorptions

Led rosso a luce fissa: 12mA

Led verde e giallo a luce fissa: 22mA

Red led with fixed light: 12mA

Yellow and green Led with fixed light: 22mA

Con luce lampeggiante tutti gli assorbimenti sono dimezzati
The whole absorptions with intermittent light are halved

Buzzer con suono continuo: 20mA

Buzzer con suono pulsante: 10 mA

Buzzer with continuous sound: 20mA
Buzzer with intermittent sound: 10 mA

